




Dayton

C-Frame Electric Motors




- Mounting: Studs from shaft end
- Two 9/64" diameter mounting holes on each side of stator
- 1 7/8" on center
- Continuous Duty
- Class B Insulation, 60hz.



<u>Model #</u>	<u>Description</u>	<u>Shaft</u>	*	<u>Stack Size</u>	<u>Amps</u>	<u>60hz Volts</u>
<u>Sleeve Bearings</u>						
4M067	1/500hp 3000RPM	3/16"x 1	CW	3/8"	0.26	115
4M068	1/250hp 3000RPM	3/16"x 1	CW	1/2"	0.41	115
4M069	1/250hp 3000RPM	3/16"x 1	CW	1/2"	0.17	230
4M070	1/150hp 3000RPM	3/16"x 1	CW	5/8"	0.54	115
4M071	1/150hp 3000RPM	3/16"x 1	CW	5/8"	0.24	230
4M072	1/100hp 3000RPM	3/16"x 1	CW	7/8"	0.62	115
4M073	1/70hp 3000RPM old # 3M606	3/16"x 1	CW	7/8"	1.16	115
4M075	1/70hp 3000RPM 2-speed, Fasco K673	3/16"x 1	CW	7/8"	1.03	115
4M074	1/70hp 3000RPM	3/16"x 1	CW	7/8"	0.48	230
4M076	1/40hp 3000RPM	1/4"x 1	CW	1.5"	1.19	115
5M064	1/20hp 3000RPM	1/4"x 1	CW	2"	2.83	115
<u>Ball Bearings</u>						
4M077	1/250hp 3000RPM	3/16"x 2 25"	CW	1/2"	0.37	115

	4M078	1/150hp 3000RPM	3/16"x 2	CW	5/8"	1.08	115
	4M079	1/70hp 3000RPM	3/16"x 2	CW	7/8"	0.96	115
	4M080	1/40hp 3000RPM	1/4"x 2	CW	1.5"	1.44	115
	5M065	1/40hp 3000RPM *7/32 x3/4"; 5/16 x 2"	Dual*		1.5"	3.98	120
	5M066	1/40hp 3000RPM 7/32x3/4" , 5/16x 2"	Dual*		1.5"	1.95	230

OEM Replacement Motors

	Model #	OEM	Description	Shaft Size	*	Stack	AMPS	60hz Volts
	4M209	Nutone C65878	1/150hp 2800RPM	7/32x 1.75"	CCW	1/2"	0.93	115
	4M210	Broan 99080207	1/150hp 2800RPM	3/16x 1 9/16"	CCW	5/8"	0.59	115
	4M180	Nutone	1/150 2750RPM	7/32x 2 5/16"	CW	11/16"	0.52	115
	4M211	Aubrey 2200-02	1/150hp 2850RPM	3/16x 1 5/16"	CW	5/8"	0.61	115
	4M212	Fasco 0648-0027	1/125hp 2750RPM	3/16x 1 1/8"	CW	1/2"	0.89	115